

The Construction Of Antenna

High sensibility, wide ranges and stable performance

Sakuma Antenna

PCBリジットアンテナ



Airsensor78 ®

Contact

304 Capital-Building, 2-25 NaKa ward, Yokohama, 231-0007

[TEL:045-211-4522](tel:045-211-4522)

E-mail: info@sakuma-ant.com

www.Sakuma-ant.com

Sakuma Antenna.

<広帯域 PCBリジット・アンテナ>

Model : JSW0318PD_Wing

--- Electrical specifications ---

- Freq band : 0.45~15.5 [GHz]
- VSWR : ≤ 3
- Impedance : 50Ω
- Gain dBi : ≤ 8 dBi
- Connector : JSM-J(female)
- RF input Power : +40dBm(10W/50Ω)
- Polarization : Linear
- Size : W:200 x H:230 x D: 245
- Weight : 410 g



